

19



Europäisches Patentamt  
European Patent Office  
Office européen des brevets

11 Veröffentlichungsnummer:

11 Publication number:

11 Numéro de publication:

0 440 077

Application No: 91 100 784.

Dieser Antrag ist nicht zur Veröffentlichung bestimmt  
und wurde deshalb zurück gezogen.

This application is not to be published and has  
therefore been withdrawn.

Cette application ne sera pas publiée  
et a donc été retirée.

**THIS PAGE BLANK (USPTO)**

(19)



Europäisches Patentamt  
European Patent Office  
Office européen des brevets



(11) Publication number:

**0 440 077 A2**

(12)

**EUROPEAN PATENT APPLICATION**(21) Application number: **91100784.7**(51) Int. Cl.<sup>5</sup>: **G06F 15/62**(22) Date of filing: **23.01.91**

(30) Priority: **25.01.90 JP 15553/90**  
**25.01.90 JP 15554/90**  
**02.03.90 JP 51047/90**  
**02.03.90 JP 51048/90**  
**02.03.90 JP 510049/90**

(43) Date of publication of application:  
**07.08.91 Bulletin 91/32**

(84) Designated Contracting States:  
**DE GB**

(71) Applicant: **TOYO INK MFG. CO., LTD.**  
**3-13, Kyobashi 2-chome**

**Chuo-ku Tokyo 104(JP)**

(72) Inventor: **Matsuki, Hiroshi**  
**12, Umezono-Cho**  
**Moriguchi-City, Osaka-Prefecture, 570(JP)**  
 Inventor: **Furusawa, Kouichi**  
**147, 3-chome, Kitahonmachi**  
**Itami-City, Hyogo-Prefecture, 664(JP)**

(74) Representative: **Reichel, Wolfgang, Dipl.-Ing.**  
**et al**  
**Reichel und Reichel Parkstrasse 13**  
**W-6000 Frankfurt am Main 1(DE)**


(54) **Image processing apparatus.**

(57) The image processing apparatus of this invention includes a novel data processing unit and memory unit. The data processing unit includes a two- to one-dimensional address coordinate value transformation unit, a two-dimensional coordinate transformation unit, an inter-pixel data calculation device and memory unit.

The two- to one-dimensional address coordinate value transformation unit transforms between a two-dimensional address coordinate value and a one-dimensional address coordinate value. The two-dimensional coordinate transformation unit transforms a coordinate value (x, y) on an x-y coordinate system within a predetermined area into a coordinate value (X, Y) on an X-Y coordinate system within a predetermined area. The inter-pixel data calculation unit performs a binomial operation between two pixel data.

The memory unit is arranged to have a variable bit length to be parallel accessible.

The image processing apparatus can realize good image processing without making the apparatus large in size.

**FIG. 1**

## IMAGE PROCESSING APPARATUS

## BACKGROUND OF THE INVENTION AND EVALUATION OF BACKGROUND TECHNIQUE

The present invention relates to an image processing apparatus. It is known in the art that in image processing magnified images, reduced images and rotated images or other processed images are displayed on a display device by processing a stored original digital image.

The present invention also relates to a coordinate transformation technique used in digital image processing, and more particularly to a technique of accessing a one-dimensional address on a one-dimensional coordinate system by using a two-dimensional address on a two-dimensional coordinate system.

The present invention also relates to a coordinate transformation technique used for digital image processing and the like, and more particularly to coordinate transformation between two two-dimensional coordinate systems.

The present invention also relates to a data calculation technique used for digital image processing and the like, and more particularly to a technique for performing binary operation between two pixel data at high speed.

The present invention also relates to a data width conversion technique used for digital data processing, and more particularly to a memory unit which can cope with a change in data width.

It is known in the art that in image processing, a digital image is displayed on a display device, or other processed images such as magnified images, reduced images and rotated images are also displayed by processing a stored original image.

It is necessary for such image processing to transform the coordinate value of an address.

Transformation between one-dimensional and two dimensional coordinate systems is often used with an image processing apparatus. Conventionally hardware technique or software technique with CPUs have been used for coordinate transformation. With the hardware technique, a special image memory called a frame buffer has been used which has a fixed image size to be displayed and a predetermined image to be processed.

The above hardware transformation technique has an advantage that if an image size is fixed, the two-dimensional coordinate values of an image have a very simple correspondence with the one-dimensional coordinate values of memory addresses of actual data. However, if the image size or the pixel address is to be changed, the capacity of an image memory becomes bulky and the relation between the image coordinate values and actual one-dimensional addresses becomes complicated, leading to a difficulty of improving the image quality, image resolution, and memory use efficiency.

The above software transformation technique has a problem of an increase of programs for calculating addresses and a problem of a long processing time.

In view of the above, there has been proposed to use a coordinate transformation circuit for transforming addresses represented by two-dimensional coordinate values into one-dimensional actual addresses (refer to Japanese Patent Laid-open Publication No. 63-6645). However, a particular transformation circuit is not proposed in the Publication, and this technique has not yet realized in practice.

A two-dimensional digital image is displayed by allocating a number of pixels to a display unit in a matrix format and giving image information such as density to each pixel.

In order to edit an digital image, such as magnification, reduction, rotation, movement, and modification, it is necessary to transfer the density of each pixel of an original image to another pixel. Namely, two-dimensional coordinate transformation is required for transforming one pixel coordinate value to another pixel coordinate value.

Such transformation has been executed heretofore by hardware technique or software technique.

Although the hardware scheme takes less processing time, it limits the type of transformation to simple scheme one such as affine transformation. There is also associated with a problem of a fixed image size and position. The software scheme can freely select the type of transformation, but it poses a problem of a long processing time required for image conversion.

Texture mapping or the like that is well known for obtaining two-dimensional image of a three-dimensional image can obtain a desired converted image, but it requires complicated equations for coordinate transformation so that a hardware scheme is not suitable, and also a software scheme requires complicated programs for sequentially processing all pixels for a long time. Furthermore, even if the same transformation is executed for a plurality of images, similar calculations must be repeated for each image, thereby not reducing the processing time.

Inter-pixel data calculation in digital image processing is often executed by software with CPUs or hardware with a limited type of calculations such as addition, subtraction, multiplication, division and the combination thereof.

The software scheme takes a lot of processing time, and the hardware scheme limits applications.

5 A digital image includes a tonal image having a pixel data of a tonal value representative of the density of color, and a specified (spot) color image having a pixel data of a color discrimination number called a color number.

A tonal image includes a monochromatic binary image, monochromatic multi-value image, and a full color image composed of primary color multi-value images (four or three colors). The data width of a pixel 10 of these images generally used is 1 bit, 8 bits (1 byte), 32 bit (4 bytes) or 24 bits (3 bytes) respectively.

A specified color image is mainly used as a masking image and a tint image. The data width of a pixel of these images generally used is 1 bit or 8 bit.

As above, in digital image processing, the data width changes with the type of an image to be processed.

15 A digital processing apparatus such as a computer has a specific bus size, or the number of parallel accessible bits, and processes data in units of specific bits to obtain a better efficiency. For image processing, particularly for image processing including a prepress process, it is preferable to use, or there is often used in actual, an apparatus having a bus size capable of parallel processing 32 bits which correspond to the data width of a pixel of a full color image represented by four primary colors Y (yellow), 20 M (magenta), C (cyan), and K (black) each having 8 bit 256 tonal values.

However, as described above, the image data uses various data widths (bit length). For example, if an image processing apparatus having a bus size of 32 bits processes a pixel data of 1 byte (8 bits) width, it reads/writes the data on the four pixel unit basis. In order to read/write the data one pixel after another, the data is required to be processed by software with CPUs, resulting in a long processing time.

25 Although 8 bit data may be stored in the 32 bit space of a memory of the image processing apparatus running on the 32 bit basis, three fourth of the memory capacity becomes unused.

## SUMMARY OF THE INVENTION

30 The present invention has been made in consideration of the above circumstances. It is an object of the present invention to provide an image processing apparatus capable of providing better image processing without making the apparatus large.

It is another object of the present invention to develop a technique for transforming an address expressed by two-dimensional coordinate values into a one-dimensional actual address, and to provide an 35 image transformation method and apparatus capable of reducing a processing time by using simple devices, and a one-dimensional frame buffer using the above techniques.

It is a further object of the present invention to provide a two-dimensional coordinate transformation method and apparatus wherein not only affine transformation used for ordinary image editing such as magnification, reduction, rotation, parallel displacement, and a combination thereof, but also other trans- 40 formations of higher degree of freedom can be achieved in a short time, specifically an optional input coordinate values (x, y) can be transformed in a short time into the coordinate system (X Y) satisfying the equations

$$\begin{aligned} X &= f(x) + g(y) \\ 45 \quad Y &= h(x) + k(y) \end{aligned}$$

where  $f(x)$  and  $h(x)$  are an optional function of  $x$ ,  $g(y)$  and  $h(y)$  are an optional function of  $y$ , and the values  $x$  and  $y$  are an integer taking a value within a predetermined range, and thus, it is possible to obtain the two- 50 dimensional coordinate transformation method and apparatus capable of shortening the coordinate transformation time without using a bulky apparatus.

It is a still further object of the present invention to provide a coordinate transformation method and apparatus and an image conversion method wherein coordinate transformation can be executed at high speed which is necessary for converting, such as moving and deforming, a digital image as desired, 55 therefore, not only affine transformation but also other transformations of higher degree of freedom can be executed at high speed, and furthermore, if a same transformation is conducted for a plurality of images, it is not necessary to calculate the coordinate transformation each time a different image is used, but the results calculated once can be used for a plurality of images at very high speed as many times as desired.

It is another object of the present invention to provide an inter-pixel data calculation apparatus capable of high speed image processing by executing binary operations of a high degree of freedom at high speed while considering the characteristics of images.

It is a further object of the present invention to provide a memory unit wherein even if the data width of a pixel data or the like to be processed is not equal to the bus size, any unit number of data per one pixel corresponding to a bus size can be read/written by changing the number of memory sub-groups constituting the memory group, accordingly, it is possible to obtain a memory unit by which a data of one pixel unit can be read at a fixed time with simplified data processing and without wastefully using the memory.

To achieve the above objects, a first invention provides an image processing apparatus comprising:

a two- to one-dimensional address coordinate transformation unit for the transformation between a one-dimensional address coordinate value and a two-dimensional address coordinate value;

a two-dimensional coordinate transformation unit for transforming coordinate values (x, y) within a predetermined area on an x-y coordinate system into coordinate values (X, Y) within a predetermined area on an X-Y coordinate system;

an inter-pixel data calculation unit for calculating two pixel data; and

a memory unit.

A second invention provides a coordinate transformation method wherein a sum  $1 = f(x) + g(y)$  of functions  $f(x)$  and  $g(y)$  of two elements (x, y) is used as an address coordinate value on a one-dimensional coordinate system, said two elements being the two-dimensional coordinate values determining an address of a two-dimensional coordinate system.

A third invention provides an image coordinate transformation method comprising the steps of:

previously setting the value of  $f(x)$  to XT as an element XT<sub>x</sub>;

previously setting the value of  $g(y)$  to YT as an element YT<sub>y</sub>;

deriving XT<sub>x</sub> and YT<sub>y</sub> respectively corresponding to x and y;

adding XT<sub>x</sub> and YT<sub>y</sub> to output  $1 = f(x) + g(y)$  to thereby determine a correspondence between  $a_{x,y}$  and  $B_1$ , wherein  $a_{x,y}$  is a data of a coordinate value (x, y) on a two-dimensional coordinate system,  $b_1$  is a data of a coordinate value 1 on a one-dimensional coordinate system for a one-dimensional medium,  $f(x)$  is a function of x, XT is an x-direction address offset table for storing the value of  $f(x)$ ,  $g(y)$  is a function of y, and YT is a y-direction address offset table for storing the value of  $g(y)$ .

A fourth invention provides an image coordinate transformation apparatus comprising:

a two-dimensional address supplier for supplying a two-dimensional address x, y;

an x-direction address offset table XT for previously storing XT<sub>x</sub> for each value x;

a y-direction address offset table YT for previously storing YT<sub>y</sub> for each value y;

a x-direction address offset reader XTR for reading XT<sub>x</sub> for a given x value;

a y-direction address offset reader YTR for reading YT<sub>y</sub> for a given y value;

an adder for adding together XT<sub>x</sub> and YT<sub>y</sub> supplied from XTR and YTR; and

a calculation unit for previously setting the values of  $f(x)$  and  $g(y)$  for values x and y in said x- and y-direction address offset tables.

A fifth invention provides a one-dimensional frame buffer for an image display device, comprising:

a two-dimensional address supplier for supplying a two-dimensional address x, y, wherein the actual data of an element  $a_{x,y}$  of a two-dimensional data matrix a [X, Y] of an image is stored in a one-dimensional data matrix b in memory unit, said two matrices being related to each other by  $b_{\alpha} + (y - 1)X + (x - 1) = a_{x,y}$  where  $\alpha$  is an optional constant;

an x-direction address offset table XT for previously storing XT<sub>x</sub> for each value x;

a y-direction address offset table YT for previously storing YT<sub>y</sub> for each value y;

an x-direction address offset reader XTR for reading XT<sub>x</sub> for a given x value;

a y-direction address offset reader YTR for reading YT<sub>y</sub> for a given y value;

an adder for adding together XT<sub>x</sub> and YT<sub>y</sub> supplied from XTR and YTR; and

a calculation unit for previously setting the values of  $f(x) = x - 1$  and  $g(y) = (y - 1)X + \alpha$  for values x and y in said x- and y-direction address offset tables.

In the image coordinate transformation method and apparatus and the one-dimensional frame buffer of the first to fifth inventions, upon supplying a two-dimensional address x and y, the values of the functions  $f(x)$  and  $g(y)$  stored in the address offset tables are read. Then, the values of the functions  $f(x)$  and  $g(y)$  are added together to output the address  $1 = f(x) + g(y)$  of a one-dimensional coordinate system to thereby complete two-to one-dimensional address transformation.

A sixth invention provides a two-dimensional coordinate transformation method of performing coordinate transformation using transformation equations  $X = f(x) + g(y)$  and  $Y = h(x) + k(y)$  for the transformation of

coordinate values (x, y) or an X-Y coordinate system within a predetermined area into coordinate values (X, Y) on an X-Y coordinate system within a predetermined area where  $f(x)$  and  $h(x)$  are a function of x and  $g(y)$  and  $k(y)$  are a function of y, wherein there are provided an X-x correspondence value table  $X_x$  for storing the value of  $f(x)$  for each value x, an X-y correspondence table  $X_y$  for storing the value of  $g(y)$  for each value y, a Y-x correspondence value table  $Y_x$  for storing the value of  $h(x)$  for each value x, and a Y-y correspondence value table  $Y_y$  for storing the value of  $k(y)$  for each value y, said method comprising the steps of:

- previously storing the values of  $f(x)$  and  $h(x)$  for each value x in cells  $X_{x_x}$  and  $Y_{x_x}$  of  $X_x$  and  $Y_x$ ;
- previously storing the values of  $g(y)$  and  $k(y)$  for each value y in cells  $X_{y_y}$  and  $Y_{y_y}$  of  $X_y$  and  $Y_y$ ;
- reading the values of  $f(x)$  and  $h(x)$  for each value x from  $X_{x_x}$  and  $Y_{x_x}$ ;
- reading the values of  $g(y)$  and  $k(y)$  for each value y from  $X_{y_y}$  and  $Y_{y_y}$ ;
- outputting a sum of the read values of  $f(x)$  and  $g(y)$  as a value X, and
- outputting a sum of the read values of  $h(x)$  and  $k(y)$  as a value Y.

A seventh invention provides a two-dimensional coordinate transformation apparatus for performing coordinate transformation using transformation equations  $X = f(x) + g(y)$  and  $Y = h(x) + k(y)$  for the transformation of coordinate values (x, y) on an x-y coordinate system within a predetermined area into coordinate values (X, Y) on an X-Y coordinate system within a predetermined area, where  $F(x)$  and  $h(x)$  are a function of x and  $g(y)$  and  $k(y)$  are a function of y, said apparatus comprising:

- a two-dimensional coordinate value supplier for supplying said coordinate value (x, y);
- an X-x correspondence value table  $X_x$  for storing the value of  $f(x)$  for each value x;
- an X-y correspondence value table  $X_y$  for storing the value of  $g(y)$  for each value y;
- a Y-x correspondence value table  $Y_x$  for storing the value of  $h(x)$  for each value x;
- a Y-y correspondence value table  $Y_y$  for storing the value of  $k(y)$  for each value y;
- an X-x correspondence value reader for reading the value of a cell  $X_{x_x}$  of the X-x correspondence value table for a given value X;
- a Y-x correspondence value reader for reading the value of a cell  $Y_{x_x}$  of the Y-x correspondence value table for a given x;
- an X-y correspondence value reader for reading the value of a cell  $X_{y_y}$  of the X-y correspondence value table for a given y;
- a Y-y correspondence value reader for reading the value of a cell  $Y_{y_y}$  of the Y-y correspondence value table for a given y;
- an X coordinate value calculator for outputting a sum of the read values of cells  $X_{x_x}$  and  $X_{y_y}$  as a value X, and
- a Y coordinate value calculator for outputting a sum of the read values of cells  $Y_{x_x}$  and  $Y_{y_y}$  as a value Y.

According to the two-dimensional coordinate transformation apparatus constructed as above of the sixth and seventh inventions, the values  $f(0), f(1), \dots, f(n)$  for integer values within a predetermined area, for example, 0, 1, 2, ..., n are stored in cells  $X_{x_0}, X_{x_1}, \dots, X_{x_n}$  of the X-x correspondence value table. the values  $h(0), h(1), \dots, h(n)$  are stored in cells  $Y_{x_0}, Y_{x_1}, \dots, Y_{x_n}$  of the Y-x correspondence value table, the values  $g(0), g(1), \dots, g(m)$  for integer values within a predetermined area, for example, 0, 1, 2, ..., m are stored in cells  $X_{y_0}, X_{y_1}, \dots, X_{y_n}$  of the X-y correspondence value table, and the values  $k(0), k(1), \dots, k(n)$  are stored in cells  $Y_{y_0}, Y_{y_1}, \dots, Y_{y_n}$  of the Y-y correspondence value table. Upon sequentially supplying values (x, y), the value  $f(x)$  in the cell  $X_{x_x}$  is read by the X-x correspondence value reader, and the value  $g(y)$  in the cell  $X_{y_y}$  is read by the X-y correspondence value reader. The values  $f(x)$  and  $g(y)$  are added together by the X coordinate value calculator and outputted as X. Similarly, the values of  $h(x)$  in the cell  $Y_{x_x}$  and  $k(y)$  in the cell  $Y_{y_y}$  are read and added together to be outputted as Y. Values (X, Y) satisfying the relation  $X = f(x) + g(y)$  and  $Y = h(x) + k(y)$  are sequentially outputted to thus complete the coordinate transformation.

With the two-dimensional coordinate transformation apparatus. the time required for the transformation of one coordinate value is very short because the time corresponds to the time required for executing an addition operation once.

If the coordinate value (X, Y) is for a pixel of an image for example, and the transformation result is obtained as a pair of integers, this pair can be used as it is. However, if the pair includes at least one value having a fraction part. this fraction part is round down to obtain an integer. Namely, instead of (X, Y),  $(X', Y')$  =  $([X], [Y])$  is used.

An eighth invention provides a two-dimensional coordinate transformation method for the coordinate transformation of coordinate values (x, Y) on an x-y coordinate system into coordinate values (X, Y) on an X-Y coordinate system, comprising the steps of:

setting the data of a function  $f_{x, y}(X, Y)$  to a memory unit at the address represented by the coordinate values (x, y), said function being selected such that the values X and Y can be separately derived for given

x and y ; and

separately deriving the values X and Y from the data of the function  $f_{x,y}(X,Y)$  for the given address (x, y) and outputting the values X and Y as coordinate values (X, Y).

A ninth invention provides a coordinate transformation apparatus comprising:

5 a memory unit for storing the data of a function  $f_{x,y}(X,Y)$  and separately deriving values X and Y upon supplying a coordinate value address (x, y) ;

a processor for obtaining the data of the function  $f_{x,y}(X,Y)$  for all necessary x and y and setting the data in the memory unit ;

a reader for reading the data of the function  $f_{x,y}(X,Y)$  for a given coordinate address (x, y) ; and

10 an XY coordinate value pickup unit for separately picking up and outputting the values X and Y from the read data of the function  $f_{x,y}(X,Y)$ .

A tenth invention provides an image conversion method comprising the steps of;

Setting the data of a function  $f_{x,y}(X,Y)$  in a memory unit at a coordinate value address (x, y), said function being selected such that the values X and Y can be separately derived for given x and y;

15 transforming the coordinate values (x, y) into coordinate values (X, Y) in accordance with a coordinate transformation method by which the values of X and Y are separately derived from the data of the function  $f_{x,y}(X,Y)$  for a given address (x, y) and the values X and Y are outputted as the coordinate values (X, Y) ; and

20 reading data from an image memory storing an original image at the address (x, y), and writing the read data in a converted image writing memory at the address (X, Y), or reading the data from the image memory at the address (X, Y), and writing the read data in the converted image writing memory at the address (x, y).

According to the coordinate transformation method and apparatus constructed as above of the eighth and ninth inventions, the data of  $f(X,Y)$  for all necessary x and y is calculated by the calculator and stored in the memory at an address (x, y). When a coordinate value (x, y) is supplied from the coordinate value supplier, the data of  $f(X,Y)$  stored in the memory at the address (x, y) is read by the reader. X and Y are separately derived by the XY coordinate value pickup device from the read data of  $f(X,Y)$  to output as a coordinate value (X, Y).

30 According to the image conversion method arranged as above of the tenth invention, there are provided the coordinate transformation apparatus and two image memories. In accordance with the supplied coordinate value (x, y), the image conversion is effected in the following manner. The image data is read from the image memory storing an original image at the address (x, y). The read image data is written in the other image memory at an address (X, Y). Alternatively, the image data is read from the image memory storing the original image at the supplied coordinate value address (X, Y), and the read image data is written in the other image memory at the address (x, y).

An eleventh invention provides an inter-pixel data calculation apparatus comprising:

a first pixel data supplier for supplying a pixel data A composed of a plurality type of element data;

a second pixel data supplier for supplying a pixel data B composed of a plurality type of element data;

a plurality of first element data selectors connected to the output side of said first pixel data supplier for

40 selecting one of said plurality of element data from said supplied pixel data A;

a plurality of second element data selectors connected to the output side of said second pixel data supplier for selecting one of said plurality of element data from said supplied pixel data B;

a plurality of binomial operation devices each connected to the output side of one of said first element data selectors for selecting an element data of said pixel data A and to the output side of one of said second element data selectors for selecting an element data of said pixel data B, for outputting the result of the binomial operation between the selected two element data; and

45 a calculator for setting the type of an element data to be selected by said element data selector and setting the type of the binomial operation to be performed by said binomial operation device.

According to the inter-pixel data calculation apparatus constructed as above of the eleventh invention, prior to inter-pixel data calculation, the calculator sets the type of element data to be selected by the element data selector and thereafter processed and the type of binomial operation to be carried out by the binomial operation unit, respectively in accordance with the type of inter-pixel data calculation to be performed.

Next, when the pixel data A is supplied from the pixel data supplier to the plurality of element data selectors, each element data selector selects one element data previously set.

Similarly, when the pixel data B is supplied from the pixel data supplier to the plurality of element data selectors, each element data selector selects one element data to be processed and previously set.

The element data selected from the pixel data A and B is inputted to the binomial operation unit and



undergoes the binomial operation to output the result.

If desired, different binomial operations may be executed in parallel at different binomial operation units to thereby reduce the processing time. If each binomial operation unit is constructed of a calculation result table and a reader, the calculation results of all necessary binomial operations are previously stored in the calculation result tables. In accordance with a combination of two element data values selected by the element data selectors from the pixels A and B, the binomial operation results for the two element data values are read from the calculation result tables and outputted, to thereby allow high speed processing.

A twelfth invention provides a memory unit comprising;

a memory comprising  $n$  memory sub-groups each having a capacity of  $k$  bits  $\times$   $m$  words, said sub-groups being assigned  $m$  word numbers  $0, 1, 2, \dots, m - 1$  and said word being constructed of  $k$  bits accessible in parallel;

a memory group selecting unit for grouping said  $n$  memory sub-groups into  $n/s$  memory groups each having  $s$  ( $s \leq n$ ) memory sub-groups capable of parallel reading/writing, said memory groups being assigned memory group numbers  $0, 1, 2, \dots, (n/s) - 1$ ; and

a memory read/write unit for parallel reading/writing the memory portion of  $k \times s$  bits designated by an address which is obtained from a combination of said memory group number and said word number.

According to the memory unit constructed as above of the twelfth invention, for example, one memory sub-group is constructed of eight parallel connected memory chips each having  $1 \text{ bit} \times 1 \text{ M words}$ . If 32 memory sub-groups are used ( $k = 8, m = 1 \text{ M}, n = 32$ ), the number  $s$  of memory sub-groups of the memory group is changed with the data width of a pixel data to be processed, e.g., the number  $s$  being set to 4 (accordingly the number of memory groups is 8) for the 32 bit data width and the number  $s$  being set to 1 (accordingly the number of memory groups is 32) for the 8 bit data width, to thereby read/write data one word after another from one memory group.

In the former case, a data having the data width of 32 bits is processed as a 32 bit data so that an apparatus having a 32 bit bus size can be used without modifying it. Also in the latter case, a data having the data width of 8 bits or 1 bit can be processed as a 32 bit data. In this case however, the remaining bits other than 8 bits or 1 bit are read/written as invalid data. In both cases, a unit data can be read/written during a predetermined time period and processed efficiently.

## BRIEF DESCRIPTION OF THE DRAWINGS

- Fig. 1 shows the outline of the image processing system of this invention;  
 Fig. 2 illustrates the structure of a coordinate transformation apparatus;  
 Fig. 3 illustrates a relationship between position of a pixels on a virtual two-dimensional image and on a one-dimensional memory;  
 Fig. 4 illustrates the structure of an image conversion apparatus;  
 Fig. 5 shows examples of various images converted by using various coordinate transformation equations;  
 Fig. 6 illustrates a virtual two-dimensional image obtained by applying the coordinate transformation apparatus to an input unit of a scanner;  
 Fig. 7 illustrates the contents of a one-dimensional memory storing a plurality of image information;  
 Fig. 8 is a view explaining the relationship between the addresses of the image information on a screen and on a one-dimensional memory;  
 Fig. 9 shows the structure of a two-dimensional coordinate transformation apparatus;  
 Fig. 10 shows the structure of the image conversion apparatus equipped with the two-dimensional coordinate transformation apparatus;  
 Fig. 11 shows an original image;  
 Fig. 12 shows a converted image of the original image shown in Fig. 11;  
 Fig. 13 illustrates how tables are set and the relationship between coordinate values of an original image and a converted image, for the case the two-dimensional coordinate transformation is affine transformation;  
 Fig. 14 shows various images converted by the two-dimensional coordinate transformation apparatus;  
 Fig. 15 is a block diagram showing the coordinate transformation apparatus;  
 Fig. 16 illustrates the relationship between data  $f_{x,y}(X, Y)$  and address  $(x, y)$  of a memory unit;  
 Fig. 17 shows the apparatus used for practicing the image conversion method of this invention;  
 Fig. 18 illustrates the relationship between an image and addresses  $(x, y)$  and  $(X, Y)$  in the apparatus shown in fig. 17;  
 Fig. 19 shows an original image;  
 Figs. 20(a) to 20(c) illustrate a memory unit wherein the data of  $f_{x,y}(X, Y)$  to be stored at the address  $(x,$

y) is expressed as decimal values X and Y, with different examples being shown in Figs. 20(a) to 20(c); Figs. 21(a) to 21(c) show converted images when values X and Y shown in Figs. 20(a) to 20(c) are outputted;

Figs. 22(a) to 22(g) show examples of images converted in accordance with the image conversion method, wherein Fig. 22(a) shows an original image, and Figs. 22(b) to 22(g) show converted images therefrom;

Fig. 23 illustrates an embodiment wherein as the data of  $f_{x,y}$  (X, Y) the data read with a color scanner is used;

Fig. 24 is a block diagram of the inter-pixel data calculation apparatus of this invention;

Fig. 25 is a schematic illustration in block form explaining a method of obtaining a transparent overlapped image by using the inter-pixel data calculation apparatus shown in Fig. 24;

Fig. 26 is a schematic illustration in block form explaining a method of obtaining a crop-masked image by using the inter-pixel data calculation apparatus shown in Fig. 24;

Fig. 27 illustrates how values are set in the calculation result table;

Fig. 28 is a block diagram showing the memory unit of this invention;

Fig. 29 shows an example of the structure of a memory of the memory unit shown in Fig. 28;

Fig. 30 shows address signal lines of the memory of the memory unit shown in Fig. 28;

Fig. 31 is a plane view explaining an example of arrangement of memory groups of the memory;

Fig. 32 is a plane view explaining another example of arrangement of memory groups of the memory;

Fig. 33 is a plane view explaining an example of arrangement of the memory sub-group; and

Fig. 34 illustrates a crop-masking method using the data width variable memory unit of this invention.

#### DESCRIPTION OF THE PREFERRED EMBODIMENTS

The embodiments of this invention will be described with reference to the accompanying drawings.

Referring to Fig. 1, an image processing apparatus generally designated by reference numeral 1 is constructed of an image coordinate value generator 2, a two-dimensional coordinate transformer 12 for transforming between coordinate values (x, y) within a predetermined area of x-y coordinate system and coordinate values (X, Y) within a predetermined area of X-Y coordinate system, a two- to one-dimensional coordinate transformer 11 for transforming two-dimensional coordinate values into one-dimensional coordinate values on a memory space, a memory unit 17 for storing an image, a inter-pixel data calculator 14 for calculating two pixel data, and a CPU 3 for initializing the calculator and performing other control operations.

Images 7, 8 and 9 are formed on the memory unit 17. The images 7 and 8 are combined or synthesized to write another image 9 on the memory unit 17 by calculating pixel data of the two images 7 and 8 by the pixel data calculator 14.

Two-dimensional coordinate values of an object pixel of each image are generated by the image coordinate value generator 2 and transformed into other two-dimensional coordinate values by two two-dimensional coordinate value transformers 12 and 12. The transformed two-dimensional coordinate values are supplied to the two- to one-dimensional coordinate value transformer 11 and transformed into a memory address for the read/write of the pixel on the memory unit.

Three memory devices 17 as shown in Fig. 1 may be combined into a single memory unit, and two two-dimensional coordinate value transformers 12 may have the same structure or may be constructed different from each other.

The number of two-dimensional coordinate value transformers 12, two- to one-dimensional coordinate value transformers 11, memory unit 17, and inter-pixel data calculators 14 may be increased to realize an image synthesizing apparatus, or may be decreased to realize an image modifying apparatus.

The coordinate transformation method and apparatus of the second to fourth inventions will be described.

Referring to Fig. 1, reference numeral 11 represents a coordinate transformer which is constructed of a two-dimensional address supplier 22, an x-axis address offset reader 23, a y-direction address offset reader 24, an address offset table 25, an adder 26, a memory read/write device 27, and a one-dimensional memory medium 28.

The address offset table 25 is constructed of an x-direction address offset table 31 and an a y-direction address offset table 32.

Prior to the activation of the coordinate transformer 11, all coordinate values (x, y) are set by another device such as a microcomputer 33 in the y- and x-direction address offset tables 31 and 32 in the form of:  $XT0 = f(0)$ ,  $XT1 = f(1)$ ,  $XT2 = f(2)$ , ...,  $XTn = f(n)$ , and  $YT0 = g(0)$ ,  $YT1 = g(1)$ ,  $YT2 = g(2)$ , ...,  $YTm = g(m)$ , where  $x = 0$  to  $n$  and  $y = 0$  to  $m$ . The x- and y-direction address offset tables 31 and 32 are constructed of a RAM, ROM or the like.

Addresses  $x$  and  $y$  or two-dimensional coordinate values  $x$  and  $y$  are supplied from the two-dimensional address supplier 22. Values  $XT_x$  and  $YT_y$  are read by the  $x$ -direction and  $y$ -direction address offset readers 23 and 24, and supplied to the adder via  $x$ - and  $y$ -direction data offset paths 44 and 45 to obtain a transformed one-dimensional address 1 which is then supplied via a one-dimensional coordinate value path 46 to the memory read/write device serving as an input/output port of the real memory, to thereby input/output actual data. In the above manner, the coordinate transformation between two- to one-dimensional coordinate values can be achieved which satisfies the transformation equation  $f(x) + g(y) = 1$ .

Fig. 3 conceptually illustrates the relationship between one- and two-dimensional images according to the invention as described with Fig. 2. Assuming that the two-dimensional coordinate values  $x$  and  $y$  shown in Fig. 2 take an optional integer value, the one-dimensional image 35 on the one-dimensional memory medium 28 that include pixel 34 of Fig. 3 can be considered as transformed into a virtual two-dimensional image 36. Thus, with this apparatus of the invention, a two-dimensional image on the  $x$ - $y$  plane can be dealt without considering the presence or structure of the one-dimensional actual memory.

Fig. 4 shows an example of an apparatus wherein two coordinate transformers 11 of this invention are used to modify a two-dimensional image and obtain a new synthesized two-dimensional image. Reference numeral 37 represents an image address generator which generates all coordinate values of an image by repeating the operations of changing  $x$  from 0 to the maximum value with increment of 1, and then incrementing  $y$  by 1 and changing  $x$  from 0 to the maximum value and so on. With the above operations, an image defined by a coordinate transformer 11a (for reading an image) is read and written on an image defined by a coordinate transformer 11b (for writing an image). Depending upon the contents of the address offset table 25 of the coordinate transformers 11a and 11b with values for  $f(x)$  and  $g(y)$  being set, an image can be modified in various ways to obtain a new image. In the two coordinate transformers 11a and 11b shown in Fig. 4, a portion of one transformers may be used by the other, if possible.

Fig. 5 shows examples of address offset data for  $f(x)$  and  $g(y)$ . The one-dimensional coordinate data (1) can be modified to two-dimensional coordinate data (2) to (8) depending on the set values of  $f(x)$  and  $g(y)$ .

If transformation into a one-dimensional image on a memory of this invention is applied to an image input/output device such as an image scanner, a pixel serially inputted from the image input/output device can be dealt as a two-dimensional image.

Fig. 6 shows an example of a scanner embodying this invention. In this example, the input port of the scanner is allocated to a virtual memory space (called a memory mapped I/O scheme), the address thereof being assumed as  $A_0$ .

If a combination of a plurality of coordinate transformers and image processing units is used, calculation between a plurality of two-dimensional images can be carried out at high speed.

Further, according to the present invention, a one-dimensional memory can be used efficiently when a plurality of different images are present on a one-dimensional memory. For example as shown in Fig. 7, two-dimensional images having consecutive pixels as indicated at (2) and (3) can be stored efficiently in the one-dimensional image at optional addresses thereof by suitably arranging them through the two- to one-dimensional address transformation using the present apparatus.

The coordinate transformation apparatus of this invention can be used as an image display frame buffer. The frame buffer according to the fifth invention will be described. A frame buffer is generally an image memory for a one frame of display device. Such a frame buffer can be realized by a one-dimensional address memory and the image transformation apparatus of this invention. Specifically, in a two-dimensional data matrix  $a$  [ $X$ ,  $Y$ ] constituting one frame of an image. It is assumed that:

(1) actual data of an element  $a_{x,y}$  is present on a one-dimensional medium  $[1]$ ,

(2) elements of  $a$  are arranged from an optional element  $b_{\alpha}$  as

(3)  $B_{\alpha} = a_{1,1}$ ,  $b_{\alpha+1} = a_{2,1}$ ,  $b_{\alpha+2} = a_{3,1}$ , ...,  $b_{\alpha+x-1} = a_{x,1}$  for all elements in the first column

(4) and  $b_{\alpha x} = a_{1,2}$ ,  $b_{\alpha+x+1} = a_{2,2}$ , ...,  $b_{\alpha+2x-1} = a_{x,2}$  for all elements in the second column,

(5) with the relationship  $b_{\alpha+(y-1)x+(x-1)} = a_{x,y}$  being

(6) generally established up to row  $Y$ .

In this case, the coordinate transformation apparatus of this invention is arranged in the following manner:

(a) so as to make the element at the column  $y$  and at the first row in the matrix  $a$  correspond with

(b) the element  $b_{\alpha+(y-1)x}$  of the matrix  $b$ ,

(c) there is set as  $g(y) = (y-1) \cdot X + \alpha$ ,

(d) so as to make  $b_{\alpha+(y-1)x+(x-1)}$  corresponding to the  $y$  column and the  $x$  row of the matrix  $a$  to indicate.

(e) relative to  $b_{\alpha+(y-1)x}$  corresponding to the  $y$  column and the first row of the matrix  $a$ ,

(f) a relative element number,

(g) there is set as  $f(x) = x - 1$ ,

(h) the two equations are set in the address offset table of the apparatus shown in Fig. 2,

(i) to thereby set XT and YT therein, and

(j) upon supplying x and y from the two-dimensional address supplier 22 to the address offset readers 23 and 24,

5 (k) to the position where the actual data for the element  $a_{xy}$  of the two-dimensional data matrix.

(l) there is outputted the value 1 for the element  $b_1$  of the one-dimensional medium b.

By using the values x and y as the coordinate values of the frame buffer (or image) and the value 1 as the memory address of the frame buffer, the coordinate transformation apparatus of this invention can be used as a frame buffer for a general purpose image display device.

10 In the above-described embodiments, an address offset table with f(x) and g(y) being set has been used for deriving the one-dimensional coordinate values. Instead of using the address offset table, the values f(x) and g(y) may be derived using a calculation device.

According to the invention, since two-dimensional image information is stored in a one-dimensional storage medium, the size and position of an image to be processed can be set as desired. Furthermore, 15 since address transformation between one- and two-dimensional addresses is realized by the hardware address offset table, two- to one-dimensional coordinate transformation can be performed at high speed, thereby allowing high speed large capacity image processing. Furthermore, by selecting suitable coordinate transformation equations, image modification (rotation in unit of 90 degrees, mirroring, magnification, reduction and the like) can be easily achieved. Still further, the actual image position on the memory can be 20 set as desired in accordance with the column or row defining image information on a two-dimensional coordinate system. Thus, the one-dimensional memory can be used efficiently for the case where there are a plurality of images to be stored.

Next, there will be described the two-dimensional coordinate transformation method and apparatus according to the sixth and seventh inventions.

25 In Fig. 9, reference numeral 12 represents a two-dimensional coordinate transformation apparatus.

The two-dimensional coordinate transformation apparatus 12 is coupled with a two-dimensional coordinate value supplier 52 which can generate coordinate values (x, y) of an integer within a predetermined area of the x-y coordinate system, e. g., the area represented by  $0 \leq X \leq n$  and  $0 \leq y \leq m$ .

The value m is the maximum value x of the coordinate values (x, y) of a pixel of a digital image, for 30 example, the value m is an integer 255, and the value n is the maximum value y such as 255.

The two-dimensional coordinate transformation apparatus 1 is provided with an X-x correspondence value table 53, a Y-x correspondence value table 55, an x-y correspondence value table 54, and a Y-y correspondence value table 56. The X-x correspondence value table 53 stores cells  $Xx_0, Xx_1, \dots, Xx_n$  representing values  $f(0), f(1), \dots, f(n)$  for the integer x within the predetermined area, respectively. The Y-x 35 correspondence value table 55 stores cells  $Yx_0, Yx_1, \dots, Yx_n$  representing values  $h(0), h(1), \dots, h(n)$  for the integer x, respectively. The X-y correspondence value table 54 stores cells  $Xy_0, Xy_1, \dots, Xy_m$  representing values  $g(0), g(1), \dots, g(m)$  for the integer y within the predetermined area, respectively. The Y-y correspondence value table 56 stores cells  $Yy_0, Yy_1, \dots, Yy_m$  representing values  $k(0), k(1), \dots, k(m)$  for the integer y, respectively.

40 The values of the Xx, Yx, Xy, and Yy correspondence value tables 53, 55, 54, and 56 are calculated by an external processor (CPU) 60 or the like and stored therein, prior to the execution of coordinate transformation.

The two-dimensional coordinate transformation apparatus 12 is also provided with an X-x correspondence value reader 57 for reading the value of each cell  $Xx_x$  of the X-x correspondence value table 53 45 corresponding to the supplied value x, a Y-x correspondence value reader 61 for reading the value of each cell  $Yx_x$  of the Y-x correspondence value table 55 corresponding to the supplied value x, an X-y correspondence value reader 58 for reading the value of each cell  $Xy_y$  of the X-y correspondence value table 54 corresponding to the supplied value y, and a Y-y correspondence value reader 62 for reading the value of each cell  $Yy_y$  of the Y-y correspondence value table 56 corresponding to the supplied value y. The 50 two-dimensional coordinate transformation apparatus 12 is also provided with an X coordinate value calculator 63 for outputting X which is a sum of the values read from the cell  $Xx_x$  and the cell  $Xy_y$  and a Y coordinate value calculator 64 for outputting Y which is a sum of the values read from the cell  $Yx_x$  and the cell  $Yy_y$ .

Next, the description will be given for the method of transforming the two-dimensional coordinate values 55 (x, y) into the two-dimensional coordinate values (X, Y) using the two-dimensional coordinate transformation apparatus 12.

First, the functions f(x), g(y), h(x), and k(y) are determined and set in the tables 53, 54, 55, and 56. Specifically,

the values  $f(0), f(1), f(2), \dots, f(n)$  are stored in the cells  $Xx_0, Xx_1, Xx_2, \dots, Xx_n$ , respectively;  
 the values  $g(0), g(1), g(2), \dots, g(m)$  are stored in the cells  $Yy_0, Yy_1, Yy_2, \dots, Yy_m$ , respectively;  
 the values  $h(0), h(1), h(2), \dots, h(n)$  are stored in the cells  $Yx_0, Yx_1, Yx_2, \dots, Yx_n$ , respectively; and  
 the values  $k(0), k(1), k(2), \dots, k(m)$  are stored in the cells  $Yy_0, Yy_1, Yy_2, \dots, Yy_m$ , respectively;

5 The two-dimensional coordinate value supplier 52 then supplies coordinate values  $(x, y)$  of an integer within the area defined by  $0 \leq x \leq n$  and  $0 \leq y \leq m$  on the  $x$ - $y$  coordinate system.

In this case the coordinate values  $(0, 0), (0, 1), \dots, (m, n)$  are supplied by first setting  $y = 1$  and changing  $x$  as  $0, 1, 2, \dots, n$ , next incrementing the value  $y$  by 1 and setting  $y = 2$  and changing  $x$  as  $0, 1, 2, \dots, n$ , then sequentially incrementing the value  $y$  by 1 and changing  $x$  as  $0, 1, 2, \dots, n$ .

10 Of the supplied coordinate values  $(x, y)$ , the value  $x$  is inputted to the  $X$ - $x$  correspondence value table 53 and the  $Y$ - $x$  correspondence value table 55 and is read from the  $X$ - $x$  correspondence value reader 57 and the  $Y$ - $x$  correspondence reader 61 to obtain the values  $f(x)$  and  $h(x)$  respectively stored in the cells  $Xx_x$  and  $Yx_x$ . The value  $f(x)$  is inputted to the  $x$  coordinate value calculator 63, and the value  $h(x)$  is inputted to the  $Y$  coordinate value calculator 64.

15 On the other hand, the value  $y$  is inputted to the  $x$ - $y$  correspondence value table 58 and the  $Y$ - $y$  correspondence value table 56 and is read from the  $X$ - $y$  correspondence value reader 58 and the  $Y$ - $y$  correspondence value reader 62 to obtain the values  $g(y)$  and  $k(y)$  respectively stored in the cells  $Xy_y$  and  $Yy_y$ . The value  $g(y)$  is inputted to the  $X$  coordinate value calculator 63, and the value  $k(y)$  is inputted to the  $Y$  coordinate value calculator 64.

20 The  $X$  coordinate value calculator 63 adds together the values  $f(x)$  and  $g(y)$  to output as  $X$  the values  $f(x) + g(y)$ .

The  $Y$  coordinate value calculator 64 adds together the values  $h(x)$  and  $k(y)$  to output as  $Y$  the values  $h(x) + k(y)$ .

In the above manner, the coordinate transformation from the system  $(x, y)$  to the system  $(X, Y)$  is  
 25 completed.

An image conversion unit 13 shown in Fig. 10 uses the coordinate transformation method and apparatus of this invention. With this image conversion unit 13, the coordinate values  $(x, y)$  generated by the two-dimensional coordinate value supplier 52 connected to the two-dimensional coordinate transformation apparatus 12 are sequentially supplied to a converted image writing memory 65 as its two-dimensional  
 30 address  $(x, y)$ .

The coordinate values  $(x, y)$  are also supplied to the coordinate transformation apparatus 12 to transform them into the coordinate values  $(X, Y)$  which are supplied to an original image recording memory 66. Image information (tonal value and the like) stored in the memory 66 at the supplied two-dimensional address  $(X, Y)$  is then read therefrom and written in the converted image writing memory 65 at the address  
 35  $(x, y)$ .

An example of such image conversion will be given below.

It is assumed that  $n = 36$ ,  $m = 32$ , and the function  $f(x)$  is set to have a particular value for each  $x$  as in the following:

40  $f(0) = 0, f(1) = 1, f(2) = 1, f(3) = 2, f(4) = 3, f(5) = 2, f(6) = 1, f(7) = 1, f(8) = 4, f(9) = 0,$   
 $f(10) = 0, f(11) = 4, f(12) = 0, f(13) = 0, f(14) = 0, f(15) = 0, f(16) = 0, f(17) = 5, f(18) = 6, f(19) = 5,$   
 $f(20) = 0, f(21) = 0, f(22) = 0, f(23) = 0, f(24) = 0, f(25) = 4, f(26) = 0, f(27) = 0, f(28) = 4, f(29) = 1,$   
 $f(30) = 1, f(31) = 2, f(32) = 3, f(33) = 2, f(34) = 1, f(35) = 1, \text{ and } f(36) = 0.$

It is also assumed that the function  $k(y)$  is set to have a particular value for each  $y$  as in the following:

45  $k(0) = 0, k(1) = 0, k(2) = 1, k(3) = 1, k(4) = 2, k(5) = 3, k(6) = 2, k(7) = 1, k(8) = 1, k(9) = 4,$   
 $k(10) = 0, k(11) = 0, k(12) = 4, k(13) = 0, k(14) = 0, k(15) = 5, k(16) = 6, k(17) = 5, k(18) = 0, k(19) = 0,$   
 $k(20) = 4, k(21) = 0, k(22) = 0, k(23) = 4, k(24) = 1, k(25) = 1, k(26) = 2, k(27) = 3, k(28) = 2, k(29) = 1,$   
 $k(30) = 1, k(31) = 0, \text{ and } k(32) = 0.$

50 The relationship between the  $X$ - $x$  and  $Y$ - $y$  correspondence value tables 53, 56 is shown in Fig. 12. In this example, it is also assumed that  $g(y) = 0$ , and  $h(x) = 0$ . Namely, the functions  $g(y)$  and  $h(x)$  always take a value 0 so that 0 is stored in all the cells  $Xy_0, Xy_1, Xy_2, \dots, Xy_m$  and all the cells  $Yx_0, Yx_1, Yx_2, \dots, Yx_n$  respectively of the  $X$ - $y$  correspondence value table 54 and the  $Y$ - $x$  correspondence value table 56.

Accordingly, the correspondence between  $X$  and  $x$  is represented only by the  $X$ - $x$  correspondence value  
 55 table 53, and the correspondence between  $Y$  and  $y$  is represented only by the  $Y$ - $y$  correspondence value table 56 (see Fig. 12).

With the above arrangement, the coordinate transformation from the system  $(x, y)$  into the system  $(X, Y)$  therefore becomes as shown in the following table at the left column.

	$(x, y) \rightarrow (X, Y)$	:	Image information of Pixel $(X, Y)$
5	$(0, 0) \rightarrow (0, 0)$	:	0
	$(0, 1) \rightarrow (0, 0)$	:	0
10	$(0, 2) \rightarrow (0, 1)$	:	0
	$(0, 3) \rightarrow (0, 1)$	:	0
	$(0, 4) \rightarrow (0, 2)$	:	0
15	$(0, 5) \rightarrow (0, 3)$	:	0
. . . . .			
20	$(1, 0) \rightarrow (1, 0)$	:	0
	$(1, 1) \rightarrow (1, 0)$	:	0
	$(1, 2) \rightarrow (1, 1)$	:	0
25	$(1, 3) \rightarrow (1, 1)$	:	0
	$(1, 4) \rightarrow (1, 2)$	:	0
30	$(1, 5) \rightarrow (1, 3)$	:	0
	$(1, 6) \rightarrow (1, 2)$	:	0
	$(1, 7) \rightarrow (1, 1)$	:	0
35	$(1, 8) \rightarrow (1, 1)$	:	0
	$(1, 9) \rightarrow (1, 4)$	:	1
40	$(1, 10) \rightarrow (1, 0)$	:	0
. . . . .			
45	$(2, 0) \rightarrow (1, 0)$	:	0
. . . . .			

50

55

	(2, 8) → (1, 1)	:	0
	(2, 9) → (1, 4)	:	1
5	(2, 10) → (1, 0)	:	0
	.....		
10	(3, 8) → (2, 1)	:	0
	(3, 9) → (2, 4)	:	1
	(3, 10) → (2, 0)	:	0
15	.....		
	(4, 8) → (3, 1)	:	0
20	(4, 9) → (3, 4)	:	1
	(4, 10) → (3, 0)	:	0
	(4, 11) → (3, 0)	:	0
25	(4, 12) → (3, 4)	:	1
	.....		
30	(4, 15) → (3, 5)	:	1
	(4, 16) → (3, 6)	:	1
	(4, 17) → (3, 5)	:	1
35	(4, 18) → (3, 0)	:	1
	.....		
40	(36, 36) → (0, 0)	:	0

A binary image original image 67 shown in Fig. 11 and taking "1" (dark) at an address indicated by shadowed parts is converted into the image 68 shown in Fig. 12.

Specifically, as the (x, y) coordinate values (0, 0), (0, 1), (0, 2), (0, 3),... are sequentially supplied, the corresponding addresses (X, Y) of the original image recording memory 66 are supplied as (0, 0), (0, 0), (0, 1), (0, 1),... with the same address being allowed to be supplied plural times. Therefore, the image information 0 (bright), 0 (bright), 0 (bright), (bright),... is sequentially written in the converted image writing memory 65 at the addresses (0, 0), (0, 1), (0, 2), (0, 3),... to accordingly obtain the converted image 68 shown in Fig. 12.

Fig. 13 illustrates the values f(x), g(y), h(x), and k(y) of the correspondence value tables where affine transformation of the system (x, y) into the system (X, Y) is executed by the two-dimensional coordinate transformation apparatus 12, with the system (X, Y) being defined by:

$$\begin{aligned} X &= ax + by + c \\ Y &= dx + ey + f \end{aligned} \quad \dots(1)$$

where a, b, c, d, e, and f are an optional constant.

The equations (1) are obtained by substituting  $f(x) = ax$ ,  $g(y) = by + c$ ,  $h(x) = dx$ , and  $k(y) = ey + f$  into

$$\begin{aligned} X &= f(x) + g(y) \\ Y &= h(x) + k(y) \end{aligned} \quad \dots(2)$$

The values are therefore set as shown in Fig. 13 for the X-x correspondence value table 53, X-y correspondence value table 54, Y-k correspondence value table 55, and Y-y correspondence value table 56. The point (4, 3) on the x-y coordinate system is transformed into a point ( $X_1$ ,  $Y_1$ ) where  $X_1 = 4a + 3b + c$  and  $Y_1 = 4d + 3e + f$ . Thus, the image information of the original image recording memory 66 at the address ( $X_1$ ,  $Y_1$ ) is written in the converted image writing memory 65 at the address (4, 3) so that an original image 67 is changed to a converted image 68 as shown in Fig. 13.

If the affine transformation is rotation, the constants a, b, c, and d take a decimal number with fraction part between -1 to 1. Therefore, the tables for  $f(x)$ ,  $g(y)$ ,  $h(x)$  and  $k(y)$  are used which can store decimal numbers with fraction part. The values of the addition results X and Y are round down to obtain integers  $X'$  and  $Y'$ .

Fig. 14 shows examples of various images converted by the image modification unit 13 wherein an original image is indicated at (a), and converted images are indicated at (b) to (h).

As appreciated from the foregoing description, not only affine transformation used for ordinary image editing such as magnification, reduction, rotation, parallel displacement, and a combination thereof, but also other transformations of higher degree of freedom can be achieved in a short time. Specifically an optional input coordinate values (x, y) can be transformed in a short time into the coordinate system (X, Y) satisfying the equations

$$\begin{aligned} X &= f(x) + g(y) \\ Y &= h(x) + k(y) \end{aligned}$$

where  $f(x)$  and  $h(x)$  are an optional function of x,  $g(y)$  and  $k(y)$  are an optional function of y, and the values x and y are an integer taking a value within a predetermined range. Thus, it is possible to obtain a two-dimensional coordinate transformation method and apparatus capable of shortening the coordinate transformation time without using a bulky apparatus. It is also possible to realize an image converter capable of converting a number of images at high speed, by using the two-dimensional coordinate transformation method and apparatus of this invention.

Next, the description will be given for the coordinate transformation method and apparatus, and the image conversion method, according to the eighth to tenth inventions.

Referring to Fig. 15, reference numeral 71 represents a coordinate transformation apparatus according to the eighth and ninth inventions. The coordinate transformation apparatus 71 is equipped with a storage device 72 having coordinate values (x, y) as its addresses. Coordinate values (X, Y) transformed from the coordinate values (x, y) are previously obtained by another means such as a CPU, and stored in the storage device 72 at corresponding addresses (x, y). Data stored in the storage device 72 is expressed as a function  $f_{x,y}(X, Y)$  by which X and Y can be easily derived separately. An example of such a function  $f_{x,y}(X, Y)$  is

$$f_{x,y}(X, Y) = x \cdot 2^\alpha + Y \quad (3)$$

where X and Y are expressed by a binary value, and  $\alpha$  is an integer larger than the number of digits of Y.

If  $\alpha$  is set as  $\alpha = 8$ , and assuming that  $X = 10100110$  and  $Y = 11000101$  for  $x = 3$  and  $y = 1$  as shown in Fig. 16, then  $f_{3,1}(X, Y) = 1010011011000101$ , the upper eight digits representing X and the lower eight digits representing Y. In this case, it is easy to separately derive X and Y from  $f_{3,1}(X, Y)$ .



Namely, the value of the function  $f_{x,y}(X, Y)$  is divided by 100000000 (binary value), and the quotient is used as X and the remainder is used as Y.

In the equation (3), although the function  $f_{x,y}(X, Y)$  is a function of X and Y and is not related to x and y, the function having a relation to x and y may also be used, for example:

$$f_{x,y}(X, Y) = x \cdot 2^x + Y + x + y \quad (4)$$

In this case, first the value of the function is subtracted by  $x + y$ , then the above-described calculation is carried out to separately derive X and Y.

It can't be considered various types of the function  $f_{x,y}(X, Y)$  which can separately derive X and Y upon input of x and y. The above example is most simple. It is obvious that a function which can not derive X and Y cannot be used, such as a function  $f_{x,y}(X, Y) = X + Y$ .

The storage device 72 may use any type of memories only if it can be accessed by the two-dimensional address (x, y). For example, the memory shown in Fig. 16 may be used whose memory cells are disposed in a one-dimensional array.

The storage device 72 stores the transformed coordinate values (X, Y) in the form of the function  $f_{x,y}(X, Y)$ . The transformed values are not associated with the type or contents of the (x, y) to (X, Y) transformation equation, and the calculation of the value of the function  $f_{x,y}(X, Y)$  is executed by a calculating device 73 if necessary.

The coordinate transformation apparatus 71 is also provided with a reader 74 for reading the data of the function  $f_{x,y}(X, Y)$  from the storage device 72 at the inputted address (x, y).

The coordinate transformation apparatus 71 is also provided with X-Y coordinate value reader 75 for separately deriving X and Y from the data of the function  $f_{x,y}(X, Y)$ . In the above example, the XY coordinate value pickup device 75 is a reader which can separately derive and output the quotient and remainder by dividing the data of the function  $f_{x,y}(X, Y)$  by binary value 100000000. Generally, the XY coordinate value pickup device 75 can use a reader of the type that X and Y can be separately derived with simple calculation matching the type of the function  $f_{x,y}(X, Y)$ . It is desirable that the type of the function  $f_{x,y}(X, Y)$  is not too much complicated and it takes less time to separately derive X and Y, from the viewpoint of the aspect of this invention. However, in principle, any function may be used if only X and Y can be separately outputted. The type of the XY coordinate value pickup device 75 is determined in accordance with the function  $f_{x,y}(X, Y)$ .

The image conversion method of the tenth invention will be described.

Referring to Fig. 17, reference numeral 81 represents an image conversion unit for practicing the image conversion method of this invention. The image conversion unit 81 is constructed of a coordinate value supplier 82, a coordinate transformation apparatus of this invention 71, and two image storage devices 83 and 84.

The coordinate value supplier 82 can sequentially generate coordinate values (0, 0), (1, 0), (2, 0), ..., (n, 0), (0, 1), (1, 1), (2, 1), ..., (n, 1), (0, 2), (1, 2), ..., (n, 2), ..., (n, m), within the necessary area of the x-y coordinate system.

The generated coordinate values (x, y) are supplied to the coordinate transformation apparatus 71 to be transformed into the coordinate values (X, Y) and also supplied to the image storage devices 83. The image storage device 83 stores an original image 85 as shown in Fig. 18. The image data  $a_{x,y}$  is read from the image storage device 83 at the supplied address (x, y).

The output (X, Y) from the coordinate transformation apparatus 71 is supplied to the image storage device 84 to thereby write the read-out image data therein at the address (X, Y). The above operations are repeated for all values (x, y) to complete image conversion.

In the above example, the address (x, y) is used for reading the original image. Instead, the address (X, Y) may be used for reading the original image. In such a case, an original image is stored in the image storage device 84 and the image data at the address (X, Y) is written in the image storage device 83 at the address (x, y).

Next, examples of converted images by the image conversion method of the tenth invention will be given. Fig. 19 shows an original image. Fig. 20 shows three different examples (a), (b), and (c) of the values X and Y, in the decimal notation, from the XY coordinate value pickup device. Fig. 21 shows the converted images using the outputs X and Y of (a), (b), and (c) in Fig. 20. If the original image of Fig. 19 is a binary value image, the images of Fig. 21 are binary images, whereas if the original image is a multi-value image, the images of Fig. 21 are multi-value images.

Fig. 22 shows other examples of converted image using the image conversion apparatus 81. Fig. 22(a)

shows an original image 83a, and Figs. 22(b) to 22(g) show converted images 84a.

As described previously, the correspondence between  $(x, y)$ , and  $(X, Y)$  can be arbitrarily set, and the data of the function  $f_{x, y}(X, Y)$  allowing separate derivation of  $X$  and  $Y$  is stored in the storage device 72 at the address  $(x, y)$ . In this connection, it is possible to use as the data of the function  $f_{x, y}(X, Y)$ , image data of a pixel at the coordinate point  $(x, y)$  read with, for example, a color scanner. Such image data is constructed of three primary color data  $R, G$  and  $B$  of multi-tone values. As shown in Fig. 23, if the  $R$  data is used as  $Y$  and the  $B$  data is used as  $X$  for image conversion, there is obtained a converted image which cannot be obtained by the above-described ordinary image conversion. In this case, an image read with the color scanner or another image may be used as the original image.

If one of the image storage devices 83 and 84 of the image conversion apparatus 81 and the reader 84 and  $XY$  coordinate value pickup unit 71 of the coordinate transformation apparatus 81 has a function to affine-transform the system  $(x, y)$  or  $(X, Y)$  to be supplied to or outputted therefrom, then a converted image can have the characteristic of the transformation of  $(x, y)$  into  $(X, Y)$  as well as of the affine transformation.

As appreciated from the foregoing description, according to the present invention, coordinate transformation can be executed at high speed which is necessary for converting, such as moving and deforming a digital image as desired. Therefore, not only affine transformation but also other transformations of higher degree of freedom can be executed at high speed. Furthermore, if a same transformation is conducted for a plurality of images, it is not necessary to calculate the coordinate transformation each time a different image is used, but the results calculated once can be used for a plurality of images at very high speed as many times as desired. As above, the present invention allows to provide the coordinate transformation method and apparatus and the image conversion method, having the above characteristic features.

Next, the inter-pixel data calculation apparatus of the eleventh invention will be described.

Referring to Fig. 24, reference numeral 14 represents an inter-pixel data calculation apparatus which is constructed of a pixel data supplier 92a for supplying a pixel data  $A$ , and a pixel data supplier 92b for supplying a pixel data  $B$ .

The pixel data  $A$  and pixel data  $B$  each are, for example, composed of four element data  $Y$  (yellow),  $M$  (magenta),  $C$  (cyan), and  $K$  (black). Each element data takes as a tonal value one of 256 values including 0, 1, 2, ..., and 255.

Connected at the output side of the pixel data supplier 92a are a plurality of, for example, four element data selectors 93a. Each of the element data selectors 93a selects a desired one of four element data from the pixel data  $A$ . The element data to be selected is previously set by a calculator 97 in accordance with what type of binomial operation is to be executed.

Similarly, connected at the output side of the pixel data supplier 92b are a plurality of, for example, four element data selectors 93b. Each of the element data selectors 93b selects a desired one of four element data from the pixel data  $B$ . The element data to be selected is previously set by the calculator 97 in accordance with what type of binomial operation is to be executed.

The outputs of one element data selector 93a and one element data selector 93b are coupled to a binomial operation device 94 for performing a binomial operation between the two element data. Each binomial operation device 94 is constructed of an operation result table 96 and a reader 95.

The operation result table 96 is a memory for storing an operation result corresponding to two element data which are used as an address to access the memory.

Values of the operation result table 96 are set for example by the calculator 97. Specifically, the calculator 97 determines the type of calculation of the binomial operation and executes the binomial operation of the determined type for all pairs of selected two element data.

The reader 95 accesses the operation result table 96 by using the designated address to thereby read and output the stored operation result.

Fig. 25 illustrates, taking transparent overlapped image as an example, how the element data selectors 93a, and 93b of the inter-pixel data calculation apparatus 14 select the element data, and how the binomial operation device 94 determines the type of calculation. The transparent overlapping of image obtains a transparent overlapped image 102 from two original images 98a and 98b transparently overlapped one upon the other.

Specifically, the four element data selectors 93a ( 93a<sub>1</sub>, 93a<sub>2</sub>, 93a<sub>3</sub>, 93a<sub>4</sub> ) select the values  $Y, M, C$ , and  $K$  (  $Y_1, M_1, C_1$ , and  $K_1$  ) among the four element data of the pixel  $A$  of the original image 98a. The four element data selectors 93b (93b<sub>1</sub>, 93b<sub>2</sub>, 93b<sub>3</sub>, 93b<sub>4</sub> ) select the values  $Y, M, C$ , and  $K$  (  $Y_2, M_2, C_2$ , and  $K_2$  ) among the four element data of the pixel  $B$  of the original image 98b. Of the four binomial operation devices 94 (94(1), 94(2), 94(3), 94(4)), the binomial operation device 94(1) receives  $Y_1$  and  $Y_2$  outputted from the element data selectors 93a<sub>1</sub> and 93b<sub>1</sub> to output  $(Y_1 + Y_2)/2$ , the binomial operation device 94(2) receives  $M_1$  and  $M_2$  outputted from the element data selectors 93a<sub>2</sub> and 93b<sub>2</sub> to output  $(M_1$

+  $M_2/2$ , the binomial operation device 94(3) receives  $C_1$  and  $C_2$  outputted from the element data selectors 93a<sub>3</sub> and 93b<sub>3</sub> to output  $(Y_1 + Y_2)/2$ , the binomial operation device 94(4) receives  $Y_1$  and  $Y_2$  outputted from the element data selectors 93a<sub>4</sub> and 93b<sub>4</sub> to output  $(K_1 + K_2)/2$ . The outputs from the binomial operation devices 94(1), 94(2), 94(3) and 94(4) are combined to obtain a pixel data C including four element data. The above operations are carried out for all pixels so that the pixel data C forms the transparent overlapped image 102 on an image display device.

Fig. 26 illustrates, taking crop-masking using a mask as an example, how the data selectors 93a and 93b select the element data, and how the binomial operation device 94 determines the type of calculation.

For crop-masking an image by using a mask, there are provided an original image 98a and a masking image 99. A crop-masking image 103 is obtained by leaving the image data of the original image 98a corresponding to a masking area 99c of the mask image, and removing the image data corresponding to an area 99d other than the masking area.

The masking image 99 is formed by pixels of a designated color (2) within the masking area 99c and pixels of another designated color (1) within the area 99d other than the masking area. The designated colors (1) and (2) are different from each other which are selected from colors registered by an image display device.

The four element data selectors 93a ( 93a<sub>1</sub> , 93a<sub>2</sub> , 93a<sub>3</sub> , 93a<sub>4</sub> select Y, M, C, and K of the four element data of the pixel data A, whereas the four element data selectors 93b ( 93b<sub>1</sub> , 93b<sub>2</sub> , 93b<sub>3</sub> , 93b<sub>4</sub> ) select the element data of the designated colors of the pixel data B of the masking image 99.

The pixel data A and B each are represented by 32 bits for example. In this case, the pixel data A is composed of four element data Y, M, C and K respectively represented by 8 bits starting from the highest-bit. The pixel data B is composed of S, D, D, and D, S being the upper 8 bits discriminating the designated colors (1) and (2), and D being dummy bits.

The binomial operation device 94(1) outputs, as the calculation result, Y when S is the designated color (2), and 0 when S is the designated color (1). The binomial operation device 94(2) outputs, as the calculation result, M when S is the designated color (2), and 0 when S is the designated color (1). The binomial operation device 94(3) outputs, as the calculation result, C when S is the designated color (2), and 0 when S is the designated color (1). The binomial operation device 94(4) outputs, as the calculation result, K when S is the designated color (2), and 0 when S is the designated color (1).

The outputs of the binomial operation devices 94(1), 94(2), 94(3), and 94(4) are inputted to the pixel data synthesizer 101 to obtain a pixel data C.

The obtained pixel data C is composed of the pixel data A of the original image 98a for those pixels within the masking area 99c, and 0 for those pixels within the area 99d outside the masking area.

Fig. 27 shows an example of data set in the calculation result table 96. For example, assuming that the binomial operation at the binomial operation device 94(1) is:

$$\sqrt{Y_1^2 + Y_2^2} \quad \dots (5),$$

the operation result of the equation (5) is stored in the table 96 at the address defined by a combination of  $Y_1$  and  $Y_2$ . The value  $Y_1$  and  $Y_2$  each take one of the values 0, 1, 2, ..., 255. The address for a given ( $Y_1$ ,  $Y_2$ ) is set as  $Y_1 * 256 + Y_2$ , and the fraction part of the calculation result is round down to obtain an integer.

As appreciated from the foregoing description, according to the present invention, the inter-pixel data calculation can be achieved simply by reading the calculation result table in which the result of the binomial operation of the element data picked up from two pixel data is stored at the address defined by a combination of the element data. Furthermore, a desired combination of types of element data is allowed, and a plurality of binomial operations can be executed in parallel. Therefore high speed image processing is possible with high speed binomial operations of a high degree of freedom while considering the characteristics of images.

Next, a memory unit according to the twelfth invention will be described.

Referring to Fig. 28, reference numeral 17 represents a memory unit. This memory unit 17 is provided with a memory 112, a memory group switching unit 113, and a memory read/write unit 115. Reference numeral 116 represents an address bus, and reference numeral 117 represents a data bus.

As shown in Fig. 29, the memory 112 is constructed of  $n$  ( $n = 32$ ) memory sub-groups 118 each having a capacity of 8 bits  $\times$  1M words capable of reading/writing  $k$  ( $k = 8$ ) bits in parallel. The memory 112 therefore has a capacity of 32 M bytes. Each memory sub-group is constructed of eight memory chips each

having a capacity of 1 bit x 1 M words.

The memory group switching unit 113 selects one of  $n/s$  memory groups 120 constituting the  $n$  ( $n = 32$ ) memory sub-groups 118 of the memory 112, where  $s$  is determined in accordance with the number ( $8 \times s$ ) of bits to be processed at a time (see to Figs. 31 and 32).

As shown in Fig. 30, the memory 112 is provided with 25 bit address signal lines 140 (MA0 to MA24). The lines MA0 to MA19 are used as word number designating lines 140a for designating one of the word numbers including 1 M words of each memory sub-group 118. The remaining 5 bit lines MA20 to MA24 are used as memory group number designating lines 140b for designating the memory group number of the memory group to be read /written. All the 5 bits lines are not necessarily used as will be described below.

Specifically, if the number of bits to be processed at a time is  $8 \times s = 32$ , then  $s = 4$  and the number of memory groups 120 is  $n/s = 8$ . In order for the memory group switching unit 113 to select one of eight memory groups sequentially disposed each constructed of contiguous four memory sub-groups, only three memory group number designating lines are required. In this case, therefore, only MA20 to MA22 lines are used, and the remaining MA23 and MA24 are not used.

If the number of bits to be processed at a time is  $8 \times s = 16$ , then  $s = 2$  and the number of memory groups is 16. In this case, therefore, four lines MA20 to MA23 are used. In another case where the number of bits is  $8 \times s = 8$ ,  $s = 1$  and the number of groups is 32. Therefore, all five lines MA20 to MA24 are used. As above, the lines MA20 to MA24 to be used are determined in accordance with the value  $s$ .

The number  $s$  of memory sub-groups constituting one memory group 120 is variably set by CPU or the like.

The memory read/write unit 115 can read/write, sequentially in the order of address, the memory portion of  $8 \times s$  bits ( $k \times s$  bits) designated by the memory group number and the word number within the memory group concerned. More in particular, the memory read/write unit 115 reads/writes the memory 112, in parallel via the address signal lines 140, in units of  $8 \times s$  bits at the  $s$  memory sub-groups of the memory group designated by the memory group number which is determined from the value  $s$ , and at the word number designated by MA0 to MA19. If  $k \times s$  bits are smaller than the data bus size such as 32 bits of an external processor, the remaining bits are read/written as invalid bits. In this manner, any unit number of data per one pixel corresponding to a bus size can be read/written by changing the number of memory sub-groups 118 constituting the memory group. Accordingly, a data of one pixel unit can be read at a fixed time without increasing the data processing time and without wastefully using the memory.

Fig. 34 illustrates a method of crop-masking an image by using three memory units of this invention, and more particularly a method of obtaining a full color image 122 by combining a full color image 121a and a masking image 121b.

First, the full color image 121a is stored in a memory unit 111a<sub>1</sub>, and the masking image 121b is stored in a memory unit 111b.

The masking image 121b is constructed of pixels each having one bit binary data which takes a binary value A or B depending upon whether the pixel is within a crop-masked area 124 colored with one of two designated colors or within a non-crop-masked area 123 colored with the other designated color.

The full color image 121a has four colors Y, M, C and K each having a data width of 8 bits, totaling 32 bits.

Data for one pixel is read from the memory unit 111a<sub>1</sub> and from the memory unit 111b, during each cycle time. If the data from the memory unit 111b is A (i.e., the pixel is within the crop-masked area 124), the data from the memory unit 111a<sub>1</sub> is written in a memory unit 111a<sub>2</sub> for storing the full color image 122 at the corresponding address. If the data from the memory unit 111b is B (i.e., the pixel is within the non-crop-masked area 123), instead of the data from the memory unit 111a<sub>1</sub>, the data 0s for all 32 bits is written in the memory unit 111a<sub>2</sub> at the corresponding address.

As appreciated from the foregoing description, according to the present invention, even if the data width of a pixel data or the like to be processed is not equal to the bus size, any unit number of data per one pixel corresponding to a bus size can be read/written by changing the number of memory sub-groups constituting the memory group. Accordingly, it is possible to obtain a memory unit by which a data of one pixel unit can be read at a fixed time with simplified data processing and without wastefully using the memory.

## Claims

1. An image processing apparatus comprising:

a two- to one-dimensional address coordinate transformation unit for the transformation between a one-dimensional address coordinate value and a two-dimensional address coordinate value;

a two-dimensional coordinate transformation unit for transforming coordinate values (x, y) within a predetermined area on an x-y coordinate system into coordinate values (X, Y) within a predetermined area on an X-Y coordinate system;

an inter-pixel data calculation unit for calculating two pixel data; and

a memory unit.

2. A coordinate transformation method wherein a sum  $1 = f(x) + g(y)$  of functions  $f(x)$  and  $g(y)$  of two elements (x, y) is used as an address coordinate value on a one-dimensional coordinate system, said two elements being the two-dimensional coordinate values determining an address of a two-dimensional coordinate system.

3. An image coordinate transformation method comprising the steps of:
  - previously setting the value of  $f(x)$  to XT as an element XT<sub>x</sub>;
  - previously setting the value of  $g(y)$  to YT as an element YT<sub>y</sub>;
  - deriving XT<sub>x</sub> and YT<sub>y</sub> respectively corresponding to x and y;
  - adding XT<sub>x</sub> and YT<sub>y</sub> to output  $1 = f(x) + g(y)$  to thereby determine a correspondence between  $a_{x,y}$  and  $b_1$ , wherein  $a_{x,y}$  is a data of a coordinate value (x, y) on a two-dimensional coordinate system,  $b_1$  is a data of a coordinate value 1 on a one-dimensional coordinate system for a one-dimensional medium,  $f(x)$  is a function of x, XT is an x-direction address offset table for storing the value of  $f(x)$ ,  $g(y)$  is a function of y, and YT is a y-direction address offset table for storing the value of  $g(y)$ .

4. An image coordinate transformation method according claim 3, wherein said functions  $f(x)$  and  $g(y)$  are determined in accordance with a positional correspondence between a data string on the two-dimensional coordinate system and a data string on the one-dimensional coordinate system of the recording medium.

5. An image coordinate transformation apparatus comprising:
  - a two-dimensional address supplier for supplying a two-dimensional address x, y;
  - an x-direction address offset table XT for previously storing XT<sub>x</sub> for each value x;
  - a y-direction address offset table YT for previously storing YT<sub>y</sub> for each value y;
  - an x-direction address offset reader XTR for reading XT<sub>x</sub> for a given x value;
  - a y-direction address offset reader YTR for reading YT<sub>y</sub> for a given y value;
  - an adder for adding together XT<sub>x</sub> and YT<sub>y</sub> supplied from XTR and YTR; and
  - a calculation unit for previously setting the values of  $f(x)$  and  $g(y)$  for values x and y in said x- and y-direction address offset tables.

6. A one-dimensional frame buffer for an image display device, comprising:
  - a two-dimensional address supplier for supplying a two-dimensional address x, y, wherein the actual data of an element  $a_{x,y}$  of a two-dimensional data matrix a [X- Y] of an image is stored in a one-dimensional data matrix b, said two matrices being related to each other by  $b_x + (y - 1)X + (x - 1) = a_{x,y}$  where  $\alpha$  is an optional constant;
  - an x-direction address offset table XT for previously storing XT<sub>x</sub> for each value x;
  - a y-direction address offset table YT for previously storing YT<sub>y</sub> for each value y;
  - an x-direction address offset reader XTR for reading XT<sub>x</sub> for a given x value;
  - a y-direction address offset reader YTR for reading YT<sub>y</sub> for a given y value;
  - an adder for adding together XT<sub>x</sub> and YT<sub>y</sub> supplied from XTR and YTR; and
  - a calculation unit for previously setting the values of  $f(x) = x - 1$  and  $g(y) = (y - 1)X + \alpha$  for values x and y in said x- and y-direction address offset tables.

7. A two-dimensional coordinate transformation method of performing coordinate transformation using transformation equations  $X = f(x) + g(y)$  and  $Y = h(x) + k(y)$  for the transformation of coordinate values (x, y) on an x-y coordinate system within a predetermined area into coordinate values (X, Y) on an X-Y coordinate system within a predetermined area, where  $f(x)$  and  $h(x)$  are a function of x and  $g(y)$  and  $k(y)$  are a function of y, wherein there are provided an X-x correspondence value table X<sub>x</sub> for storing the value of  $f(x)$  for each value x, an X-y correspondence table X<sub>y</sub> for storing the value of  $g(y)$  for each value y, a Y-x correspondence value table Y<sub>x</sub> for storing the value of  $h(x)$  for each value x, and a Y-y correspondence value table Y<sub>y</sub> for storing the value of  $k(y)$  for each value y, said method comprising the steps of;

previously storing the values of  $f(x)$  and  $h(x)$  for each value  $x$  in cells  $Xx_x$  and  $Yx_x$  of  $Xx$  and  $Yx$ ;  
 previously storing the values of  $g(y)$  and  $k(y)$  for each value  $y$  in cells  $XY_y$  and  $Yy_y$  of  $Xy$  and  $Yy$ ;  
 reading the values of  $f(x)$  and  $h(x)$  for each value  $x$  from  $Xx_x$  and  $Yx_x$ ;  
 reading the values of  $g(y)$  and  $k(y)$  for each value  $y$  from  $Xy_y$  and  $Yy_y$ ;  
 5 outputting a sum of the read values of  $f(x)$  and  $g(y)$  as a value  $X$ , and  
 outputting a sum of the read values of  $h(x)$  and  $k(y)$  as a value  $Y$ .

8. A two-dimensional coordinate transformation apparatus for performing coordinate transformation using transformation equations  $X = f(x) + g(y)$  and  $Y = h(x) + k(y)$  for the transformation of coordinate values  $(x, y)$  on an  $x$ - $y$  coordinate system within a predetermined area into coordinate values  $(X, Y)$  on an  $X$ - $Y$  coordinate system within a predetermined area, where  $f(x)$  and  $h(x)$  are a function of  $x$  and  $g(y)$  and  $k(y)$  are a function of  $y$ , said apparatus comprising:
  - a two-dimensional coordinate value supplier for supplying said coordinate value  $(x, y)$ ;
  - an  $X$ - $x$  correspondence value table  $Xx$  for storing the value of  $f(x)$  for each value  $x$ ;
  - 15 an  $X$ - $y$  correspondence value table  $Xy$  for storing the value of  $g(y)$  for each value  $y$ ;
  - a  $Y$ - $x$  correspondence value table  $Yx$  for storing the value of  $h(x)$  for each value  $x$ ;
  - a  $Y$ - $y$  correspondence value table  $Yy$  for storing the value of  $k(y)$  for each value  $y$ ;
  - an  $X$ - $x$  correspondence value reader for reading the value of a cell  $Xx_x$  of the  $X$ - $x$  correspondence value table for a given value  $x$ ;
  - 20 a  $Y$ - $x$  correspondence value reader for reading the value of a cell  $Yx_x$  of the  $Y$ - $x$  correspondence value table for a given  $x$ ;
  - an  $X$ - $y$  correspondence value reader for reading the value of a cell  $Xy_y$  of the  $X$ - $y$  correspondence value table for a given  $y$ ;
  - a  $Y$ - $y$  correspondence value reader for reading the value of a cell  $Yy_y$  of the  $Y$ - $y$  correspondence value table for a given  $y$ ;
  - 25 an  $X$  coordinate value calculator for outputting a sum of the read values of cells  $Xx_x$  and  $Xy_x$  as a value  $X$ , and
  - a  $Y$  coordinate value calculator for outputting a sum of the read values of cells  $Yx_x$  and  $Yy_y$  as a value  $Y$ .
9. A coordinate transformation method for the coordinate transformation of coordinate values  $(x, y)$  on an  $x$ - $y$  coordinate system into coordinate values  $(X, Y)$  or, an  $X$ - $Y$  coordinate system, comprising the steps of:
  - setting the data of a function  $f_{x, y}(X, Y)$  to a memory unit at the address represented by the coordinate values  $(x, y)$ , said function being selected such that the values  $X$  and  $Y$  can be separately derived for given  $x$  and  $y$ ; and
  - 35 separately deriving the values  $X$  and  $Y$  from the data of the function  $f_{x, y}(X, Y)$  for the given address  $(x, y)$  and outputting the values  $X$  and  $Y$  as coordinate values  $(X, Y)$ .
10. A coordinate transformation method according to claim 9, wherein the data of the function  $f_{x, y}(X, Y)$  is represented as  $f_{x, y}(X, Y) = X * 2^\alpha + Y$ , where  $X$  and  $y$  are represented by a binary notation and  $\alpha$  is an integer larger than the number of digits of  $Y$ .
11. A coordinate transformation method according to claim 9, wherein the data of the function  $f_{x, y}(X, Y)$  is previously set by a calculator in accordance with a transformation equation of or the correspondence between the coordinate transformation.
12. A coordinate transformation method according to claim 9, wherein the coordinate value  $(x, y)$  are the coordinate values of a pixel, inputted from a color scanner, and at least one of  $X$  and  $Y$  represents the tonal value for each color of the inputted pixel.
13. A coordinate transformation apparatus comprising:
  - a memory unit for storing the data of a function  $f_{x, y}(X, Y)$  and separately deriving values  $X$  and  $Y$  upon supplying a coordinate value address  $(x, y)$ ;
  - 55 a processor for obtaining the data of the function  $f_{x, y}(X, Y)$  for all necessary  $x$  and  $y$  and setting the data in the memory unit;
  - a reader for reading the data of the function  $f_{x, y}(X, Y)$  for a given coordinate address  $(x, y)$ ; and
  - an  $XY$  coordinate value pickup unit for separately picking up and outputting the values  $X$  and  $Y$

from the read data of the function  $f_{x,y}(X, Y)$ .

14. An image conversion method comprising the steps of:

- 5 setting the data of a function  $f_{x,y}(X, Y)$  in a memory unit at a coordinate value address  $(x, y)$ , said function being selected such that the values  $X$  and  $Y$  can be separately derived for given  $x$  and  $y$ ;
- transforming the coordinate values  $(x, y)$  into coordinate values  $(X, Y)$  in accordance with a coordinate transformation method by which the values of  $X$  and  $Y$  are separately derived from the data of the function  $f_{x,y}(X, Y)$  for a given address  $(x, y)$  and the values  $X$  and  $Y$  are outputted as the coordinate values  $(X, Y)$ ; and
- 10 reading data from an image memory storing an original image at the address  $(x, y)$ , and writing the read data in a converted image writing memory at the address  $(X, Y)$ , or reading the data from the image memory at the address  $(X, Y)$ , and writing the read data in the converted image writing memory at the address  $(x, y)$ .

15 15. An inter-pixel data calculation apparatus comprising:

- a first pixel data supplier for supplying a pixel data  $A$  composed of a plurality type of element data;
  - a second pixel data supplier for supplying a pixel data  $B$  composed of a plurality type of element data;
  - a plurality of first element data selectors connected to the output side of said first pixel data supplier for selecting one of said plurality of element data from said supplied pixel data  $A$ ;
  - 20 a plurality of second element data selectors connected to the output side of said second pixel data supplier for selecting one of said plurality of element data from said supplied pixel data  $B$ ;
  - a plurality of binomial operation devices each connected to the output side of one of said first element data selectors for selecting an element data of said pixel data  $A$  and to the output side of one of said second element data selectors for selecting an element data of said pixel data  $B$ , for outputting
  - 25 the result of the binomial operation between the selected two element data; and
  - a calculator for setting the type of an element data to be selected by said element data selector and setting the type of the binomial operation to be performed by said binomial operation device.
- 30 16. An inter-pixel data calculation apparatus according to claim 15, wherein said binomial operation device comprises a calculation result table for storing all the necessary calculation results and a reader for reading the calculation result stored in said calculation result table.

17. A memory unit comprising:

- 35 a memory comprising  $n$  memory sub-groups each having a capacity of  $k$  bit  $\times$   $m$  word, said sub-groups being assigned  $m$  word numbers  $0, 1, 2, \dots, m-1$  and said word being constructed of  $k$  bits accessible in parallel;
- a memory group selecting unit for grouping said  $n$  memory sub-groups into  $n/s$  memory groups each having  $s$  ( $s \leq n$ ) memory sub-groups capable of parallel reading/writing, said memory groups
- 40 being assigned memory group numbers  $0, 1, 2, \dots, (n/s) - 1$ ; and
- a memory read/write unit for parallel reading/writing the memory portion of  $k \times s$  bits designated by an address which is obtained from a combination of said memory group number and said word number.

45 18. A memory device according to claim 17, wherein said  $k$  bit  $\times$   $m$  words memory sub-group is constructed of a combination of memory sub-groups each having a capacity of  $t$  bits  $\times$   $u$  words ( $t \leq k, u \leq m$ ).

50 19. A memory device according to claim 17, wherein said memory group selecting unit can change said value  $s$  so that the data width  $k \times s$  and the address width  $n/s$  are made variable.

FIG. 1






FIG. 2




FIG. 3




FIG. 4






FIG. 5


(1)




(2)




(3)




(4)




(5)



(6)



(7)



(8)




FIG. 6





FIG. 7

(1)



(2)



(3)




FIG. 8




FIG. 9




FIG. 10





FIG. II








FIG. 13




FIG. 14




FIG. 15




FIG. 16




FIG. 17




FIG. 18




FIG. 19




FIG. 20




FIG. 21






FIG. 22




FIG. 23




FIG. 24




FIG. 25




FIG. 26







FIG. 27

Y1	Y2	ADDRESS	$\sqrt{Y_1^2 + Y_2^2}$
255	255	$255 \times 256 + 255 = 25536 \dots$	360
255	254	$255 \times 256 + 254 = 65535 \dots$	359
255	253	$255 \times 256 + 253 = 65534 \dots$	359
			
2	0	$2 \times 256 + 0 = 512 \dots$	2
1	255	$1 \times 256 + 255 = 511 \dots$	255
			
1	2	$1 \times 256 + 2 = 258 \dots$	2
1	1	$1 \times 256 + 1 = 257 \dots$	1
1	0	$1 \times 256 + 0 = 256 \dots$	1
0	255	$0 \times 256 + 255 = 255 \dots$	255
			
0	2	$0 \times 256 + 2 = 2 \dots$	2
0	1	$0 \times 256 + 1 = 1 \dots$	1
0	0	$0 \times 256 + 0 = 0 \dots$	0

~96

FIG. 28




FIG. 29




FIG. 30




FIG. 31






FIG. 32




FIG. 33





FIG. 34



(19)



Europäisches Patentamt  
European Patent Office  
Office européen des brevets



(11) Publication number:

**0 440 077 A3**

(12)

**EUROPEAN PATENT APPLICATION**(21) Application number: **91100784.7**(51) Int. Cl.<sup>5</sup>: **G06F 15/62, G09G 1/16**(22) Date of filing: **23.01.91**

(30) Priority: **25.01.90 JP 15553/90**  
**25.01.90 JP 15554/90**  
**02.03.90 JP 51047/90**  
**02.03.90 JP 51048/90**  
**02.03.90 JP 51049/90**

(43) Date of publication of application:  
**07.08.91 Bulletin 91/32**

(84) Designated Contracting States:  
**DE GB**

(96) Date of deferred publication of the search report:  
**23.06.93 Bulletin 93/25**

(71) Applicant: **TOYO INK MFG. CO., LTD.**  
**3-13, Kyobashi 2-chome**  
**Chuo-ku Tokyo 104(JP)**

(72) Inventor: **Matsuki, Hiroshi**  
**12, Umezono-Cho**  
**Moriguchi-City, Osaka-Prefecture, 570(JP)**  
 Inventor: **Furusawa, Kouichi**  
**147, 3-chome, Kitahonmachi**  
**Itami-City, Hyogo-Prefecture, 664(JP)**

(74) Representative: **Reichel, Wolfgang, Dipl.-Ing.**  
**et al**  
**Reichel und Reichel Parkstrasse 13**  
**W-6000 Frankfurt am Main 1 (DE)**


(54) **Image processing apparatus.**

(57) The image processing apparatus of this invention includes a novel data processing unit and memory unit. The data processing unit includes a two- to one-dimensional address coordinate value transformation unit, a two-dimensional coordinate transformation unit, an inter-pixel data calculation device and memory unit.

The two- to one-dimensional address coordinate value transformation unit transforms between a two-dimensional address coordinate value and a one-dimensional address coordinate value. The two-dimensional coordinate transformation unit transforms a coordinate value (x, y) on an x-y coordinate system within a predetermined area into a coordinate value (X, Y) on an X-Y coordinate system within a predetermined area. The inter-pixel data calculation unit performs a binomial operation between two pixel data.

The memory unit is arranged to have a variable bit length to be parallel accessible.

The image processing apparatus can realize good image processing without making the apparatus large in size.

**FIG. 1**



European Patent  
Office

## EUROPEAN SEARCH REPORT

Application Number

EP 91 10 0784

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int. Cl.5)
X	DE-A-3 726 003 (MINOLTA CAMERA K.K.)	2	G 06 F 15/62 G 09 G 1/16
Y	& US-A-5 040 129 (NISHIYAMA)	1	
A	* abstract; claims 3-7; column 4, line 27 - column 4, line 33 *	3-7	
	---		
P,Y	EP-A-0 360 155 (OKI ELECTRIC INDUSTRY CO. LTD.)	1	
P,X	* page 2, column 2, line 15 - page 2, column 2, line 48 *	14	
	---		
E,X	US-A-5 068 808 (WAKE)	8-16	
	* column 4, line 13 - column 4, line 37; column 5, line 26 - column 5, line 59 *		
	-----		
			TECHNICAL FIELDS SEARCHED (Int. Cl.5)
			G 06 F G 09 G
<del>The present search report has been drawn up for all claims</del>			
Place of search		Date of completion of the search	Examiner
THE HAGUE		18-11-1992	GONZALEZ ORDONEZ O
CATEGORY OF CITED DOCUMENTS			
X : particularly relevant if taken alone		T : theory or principle underlying the invention	
Y : particularly relevant if combined with another document of the same category		E : earlier patent document, but published on, or after the filing date	
A : technological background		D : document cited in the application	
O : non-written disclosure		L : document cited for other reasons	
P : intermediate document		& : member of the same patent family, corresponding document	



European Patent  
Office

### CLAIMS INCURRING FEES

The present European patent application comprised at the time of filing more than ten claims.

- ☐ All claims fees have been paid within the prescribed time limit. The present European search report has been drawn up for all claims.
- ☐ Only part of the claims fees have been paid within the prescribed time limit. The present European search report has been drawn up for the first ten claims and for those claims for which claims fees have been paid, namely claims:
- ☐ No claims fees have been paid within the prescribed time limit. The present European search report has been drawn up for the first ten claims.

### LACK OF UNITY OF INVENTION

The Search Division considers that the present European patent application does not comply with the requirement of unity of invention and relates to several inventions or groups of inventions, namely:

See Sheet B.

- ☐ All further search fees have been paid within the fixed time limit. The present European search report has been drawn up for all claims.
- ☐ Only part of the further search fees have been paid within the fixed time limit. The present European search report has been drawn up for those parts of the European patent application which relate to the inventions in respect of which search fees have been paid, namely claims:
- ☒ None of the further search fees has been paid within the fixed time limit. The present European search report has been drawn up for those parts of the European patent application which relate to the invention first mentioned in the claims.

namely claims: 1-16

**LACK OF UNITY OF INVENTION**

The Search Division considers that the present European patent application does not comply with the requirement of unity of invention and relates to several inventions or groups of inventions, namely:

1. Claims 1-16: Method of a system for transforming coordinates.
2. Claims 17-19: Memory system with selectable variable word length.